

FRS/GMRS Cross-reference chart

Important note: there is a channel difference between older model GMRS radios and newer ones. The following chart will detail the proper cross-referencing necessary to get all radios on the proper frequency to interconnect.

PR 1100 WX Channel Displayed	Channel NO. for GMRS models except PR 950 DX and PR 1100 WX	Type of Radio Service	Frequency in MHz	Power in Watts
1	1	FRS/GMRS	462.5625	2 or 0.5 (selectable)
2	2	FRS/GMRS	462.5875	2 or 0.5 (selectable)
3	3	FRS/GMRS	462.6125	2 or 0.5 (selectable)
4	4	FRS/GMRS	462.6375	2 or 0.5 (selectable)
5	5	FRS/GMRS	462.6625	2 or 0.5 (selectable)
6	6	FRS/GMRS	462.6875	2 or 0.5 (selectable)
7	7	FRS/GMRS	462.7125	2 or 0.5 (selectable)
8		FRS	467.5625	0.5 (only)
9		FRS	467.5875	0.5 (only)
10		FRS	467.6125	0.5 (only)
11		FRS	467.6375	0.5 (only)
12		FRS	467.6625	0.5 (only)
13		FRS	467.6875	0.5 (only)
14		FRS	467.7125	0.5 (only)
15	11	GMRS	462.5500	2 or 0.5 (selectable)
16	8	GMRS	462.5750	2 or 0.5 (selectable)
17	12	GMRS	462.6000	2 or 0.5 (selectable)
18	9	GMRS	462.6250	2 or 0.5 (selectable)
19	13	GMRS	462.6500	2 or 0.5 (selectable)
20	10	GMRS	462.6750	2 or 0.5 (selectable)
21	14	GMRS	462.7000	2 or 0.5 (selectable)
22	15	GMRS	462.7250	2 or 0.5 (selectable)